





DG1000Z Series Function/Arbitrary Waveform Generator

- SiFi (Signal Fidelity) for 100% waveform replication
- 2Mpts or 8Mpts/CH(std.), 16Mpts/CH (opt.) arbitrary waveform length
- Standard 2 full functional independent channels
- ±1ppm frequency stability, -125dBc/Hz phase noise, 200ps low jitter
- Built-in 8 orders harmonics generator
- Built-in 7 digits/s counter up to 200MHz
- 160 built-in pre-edited waveforms
- Intuitive arbitrary waveform editing software
- Full modulation supported: AM, FM, PM, ASK, FSK, PSK and PWM

DG1000Z series function/arbitrary waveform generator is a multi-functional generator that combines many functions in one, including Function Generator, Arbitrary Waveform Generator, Noise Generator, Pulse Generator, Harmonics Generator, Analog/Digital Modulator and Counter. As a multi-functional, high performance and portable generator, it will be a new selection in education, R&D, production, test and etc.



DG1000Z Series Function/Arbitrary Waveform Generator






Dimensions: Width × Height × Depth=261.5mm × 112mm × 318.4mm Weight: 3.2kg (without package)



Feature and Benefits

Standard 2 full functional channels



SiFi

Arbitrary waveform function with innovative SiFi technology



Up to 160 built-in waveforms



Burst function



Multiple analog and digital modulations



Sweep function



Standard harmonic generator



Waveform summing function



Standard 7 digits/s full function frequency counter with 200MHz bandwidth



Channels and system setting



In line with LXI Core 2011 Device



File Management Function





Specifications

All the specifications can be guaranteed if the following two conditions are met unless where noted.

- The generator is within the calibration period and has performed self-calibration.
- The generator has been working continuously for at least 30 minutes under the specified temperature (18°C ~ 28°C).

All the specifications are guaranteed unless those marked with "typical".

Model	DG1022Z	DG1032Z	DG1062Z	
Channel	2	2	2	
Max Frequency	25 MHz	30 MHz	60 MHz	
Sample Rate	200 MSa/s			
Waveform				
Basic Waveform	Sine, Square, Ramp	p. Pulse, Noise		
Built-in Arbitrary Waveform	160 kinds, including Sinc, Exponential Rise, Exponential Fall, ECG, Gauss, HaverSine, Lorentz, Dual-Tone, etc.			
Frequency Characteristics				
Sine	1 µHz to 25 MHz	1 µHz to 30 I	MHz 1 µHz to 60 MHz	
Square	1 µHz to 25 MHz	1 µHz to 25 I	MHz 1 µHz to 25 MHz	
Ramp	1 µHz to 500 kHz	1 µHz to 500	THE COURT OF THE C	
Pulse	1 µHz to 15 MHz	1 µHz to 15 l		
Harmonic	1uHz to 10 MHz	1 µHz to 10 f		
Noise (-3dB)	25 MHz bandwidth	30 MHz band		
Arbitrary Waveform	1 µHz to 10 MHz	1 µHz to 10 l		
Resolution	1 µHz	1 1 1 1 2 10 10 1	T prince to deviating	
Accuracy		g value, 18°C to 28°C		
2000 TO	pp	9		
Sine Wave Spectrum Purity				
Harmonic Distortion		ed): <-65 dBc (included): <-55 dBc (included): <-50 dBc		
Total Harmonic Distortion	<0.075% (10 Hz to 20 kHz, 0 dBm)			
Spurious (non-harmonic)	Typical (0 dBm) ≤10 MHz: <-70 dBc >10 MHz: <-70 dBc + 6 dB/octave			
Phase Noise	Typical (0 dBm, 10 kHz offset) 10 MHz: <-125 dBc/Hz			
Signal Characteristics				
Square				
	Typical (1 Vpp)			
Rise/Fall Time	Typical (1 Vpp) <10ns			
Overshoot	Typical (100 kHz, 1 Vpp) ≤5%			
Duty Cycle	0.01% to 99.99% (li	mited by the current freque	ncy setting)	
Non-symmetry	1% of the period + 5 ns			
Jitter (rms)	Typical (1 Vpp) ≤5 MHz: 2 ppm + 200 ps > 5 MHz: 200 ps			
Ramp				
Linearity	≤1% of peak output	(typical, 1 kHz, 1 VPP, 100	% symmetry)	
Symmetry	0% to 100%			
Pulse				
Pulse Width	16ns to 999.999 983	2 118ks (limited by the curr	ent frequency setting)	
Duty Cycle	0.001% to 99.999% (limited by the current frequency setting)			
Rising/Falling Edge		ne current frequency setting	, , ,	
Overshoot	Typical (1 Vpp) ≤5%	,,		
Jitter (rms)	Typical (1 Vpp) ≤5 MHz 2 ppm + 200 ps > 5 MHz 200 ps			
Arbitrary Waveform	The second secon			
Waveform Length	2Mpts (std.) 16Mpts (opt.)	8Mpts (std.) 16Mpts (opt.)	8Mpts (std.) 16Mpts (opt.)	



Function/Arbitrary Waveform Generator DG1000Z Series

	No. source
Vertical Resolution	14 bits
Sample Rate	200MSa/s
Min Rise/Fall Time	Typical (1 Vpp) <10 ns
Jitter (rms)	Typical (1 Vpp) ≤5 MHz: 2 ppm + 200 ps > 5 MHz: 200 ps
Editing Mode	Point Edit, Block Edit, Insert Waveform
Harmonic Output	
Harmonic Order	≤8
Harmonic Type	Even Harmonic, Odd harmonic, Order Harmonic, User
Harmonic Amplitude	The amplitude of each order of harmonic can be set
Harmonic Phase	The phase of each order of harmonic can be set
Output Characteristics	
Amplitude (into 50 Ω)	
Amplitude (into 50 12)	<10 MHz: 1.0 m)/nn to 10 \/nn
Range	≤10 MHz: 1.0 mVpp to 10 Vpp ≤30 MHz: 1.0 mVpp to 5.0 Vpp ≤60 MHz: 1.0 mVpp to 2.5 Vpp
Accuracy	Typical (1 kHz sine, 0 V offset, >10 mVpp, auto) ±(1% of the setting value) ±1 mV
Flatness	Typical (sine, 2.5 Vpp) ≤10 MHz: ±0.1 dB ≤60 MHz: ±0.2 dB
Unit	Vpp, Vrms, dBm
Resolution	0.1mVpp or 4 digits
Offset (into 50 Ω)	C. Hillypp of 4 digits
Range (Peak ac+dc)	1EV/nk polido
	±5Vpk ac+dc
Accuracy	±(1% of the setting value + 5mV + 0.5% of the amplitude)
Waveform Output	FO O // N
Output Impedance	50 Ω (typical)
Protection	Short-circuit protection, automatically disable the waveform output when overload occurs
Modulation Characteristics	
Modulation Type	AM, FM, PM, ASK, FSK, PSK, PWM
AM	
	The state of the s
Carrier Waveform	Sine, Square, Ramp, Arb (except DC)
Carrier Waveform Source	Sine, Square, Ramp, Arb (except DC) Internal/External
Source	Internal/External
Source Modulating Waveform Modulation Depth	Internal/External Sine, Square, Ramp, Noise, Arb
Source Modulating Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120%
Source Modulating Waveform Modulation Depth Modulating Frequency FM	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC)
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC)
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Modulating Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Modulating Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Hodulating Waveform Source Modulating Waveform Phase Deviation	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360°
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360°
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Carrier Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC)
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Key Frequency FSK Carrier Waveform Source	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulating Frequency FM Carrier Waveform Source Modulating Frequency PM Carrier Waveform Source Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Source Modulating Waveform	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square, Ramp, Arb (except DC) Internal/External
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz
Source Modulating Waveform Modulation Depth Modulating Frequency FM Carrier Waveform Source Modulating Waveform Modulating Frequency PM Carrier Waveform Source Modulating Waveform Phase Deviation Modulating Frequency ASK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency FSK Carrier Waveform Source Modulating Waveform Key Frequency	Internal/External Sine, Square, Ramp, Noise, Arb 0% to 120% 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Noise, Arb 0° to 360° 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle 2 mHz to 1 MHz Sine, Square, Ramp, Arb (except DC) Internal/External Square with 50% duty cycle



Modulating Waveform	Square with 50% duty cycle		
Key Frequency	2 mHz to 1 MHz		
PWM	- supposed to		
Carrier Waveform	Pulse		
Source	Internal/External		
Modulating Waveform	Sine, Square, Ramp, Noise, Arb		
Width Deviation	0% to 100% of the pulse width		
Modulating Frequency	2 mHz to 1 MHz		
External Modulation Input			
Input Range	75 mVRMS to ±5 Vac + dc		
Input Bandwidth	50 kHz		
Input Impedance	10ΚΩ		
Burst Characteristics	Later can proper than all excellen		
Carrier Waveform	Sine, Square, Ramp, Pulse, Noi	The state of the s	
Carrier Frequency	2mHz to 25MHz	2mHz to 30MHz	2 mHz to 60 MHz
Burst Count	1 to 1,000,000 or Infinite		
Start/Stop Phase	0° to 360°, 0.1° resolution		
Internal Period	1 μs to 500 s		
Gated Source	External Trigger		
Trigger Source	Internal, External or Manual		
Trigger Delay	0 ns to 100 s		
Sweep Characteristics			
Carrier Waveform	Sine, Square, Ramp, Arb (excep	ot DC)	
Туре	Linear, Log or Step	HI. V. V. SAAV	
Direction	Up or Down		
Start/Stop Frequency	The same with the upper/lower	limit of the corresponding carrier frequency	uency
Sweep Time	1 ms to 500 s		305 M100 FA
Hold/Return Time	0 ms to 500 s		
Trigger Source	Internal, External or Manual		
Marker	Falling edge of the sync signal (programmable)		
		programmable)	
unapassa di	,	programmable)	
	,	ргодганнале)	
Frequency Counter		-	
Frequency Counter Function	Frequency, Period, Positive/Neg	gative Pulse Width, Duty Cycle	
Frequency Counter Function Frequency Resolution	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s	gative Pulse Width, Duty Cycle	
Frequency Counter Function Frequency Resolution Frequency Range	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz	gative Pulse Width, Duty Cycle	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range	gative Pulse Width, Duty Cycle	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal)	gative Pulse Width, Duty Cycle) 5ns to 16 days	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range	gative Pulse Width, Duty Cycle 5ns to 16 days ±1.5 Vdc	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz	pative Pulse Width, Duty Cycle 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz	spative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz	sative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz	spative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz easurement	sative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz	sative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp	
Frequency Counter Function Frequency Resolution	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz loud MHz to 200 MHz leasurement 1 µHz to 25 MHz	pative Pulse Width, Duty Cycle 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc	DC Coupling
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz leasurement 1 µHz to 25 MHz Min Pulse Width	to ative Pulse Width, Duty Cycle 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns	DC Coupling
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 1 µHz to 100 MHz Min Pulse Width Pulse Width Resolution	by the pulse Width, Duty Cycle 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns	DC Coupling
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz leasurement 1 µHz to 25 MHz Min Pulse Width	to ative Pulse Width, Duty Cycle 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns	DC Coupling
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 5 MHz 100 MHz to 200 MHz 100 MHz to 25 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display)	sative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100%	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle Measurement Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz leasurement 1 µHz to 25 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display)	sative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100%	Input Impedance = 1 MΩ
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle Meanges Pulse Width Duty Cycle Input Characteristics Input Signal Range	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 5 MHz 100 MHz to 200 MHz 100 MHz to 25 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display)	gative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC	
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Signal Range	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 1 µHz to 100 MHz 1 µHz to 500 MHz 100 MHz to 200 MHz HIPz to 25 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection	pative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz	Input Impedance = 1 MΩ
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Adjustment	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 5 MHz Hasurement 1 µHz to 25 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode	spative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vpc 40 ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz -2.5V to +2.5V	Input Impedance = 1 MΩ DC
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 1 µHz to 100 MHz 1 µHz to 500 MHz 100 MHz to 200 MHz HIPz to 25 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection	pative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz	Input Impedance = 1 MΩ DC
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Adjustment	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 5 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection Trigger Level Range	pative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz -2.5V to +2.5V 0% (about 140 mV hysteresis v	Input Impedance = 1 MΩ DC
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Adjustment	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 1 µHz to 100 MHz 1 µHz to 100 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection Trigger Sensitivity Range	pative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vpc 60 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz -2.5V to +2.5V 0% (about 140 mV hysteresis v hysteresis voltage)	Input Impedance = 1 MΩ DC
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Signal Range Input Adjustment Input Trigger	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection Trigger Sensitivity Range GateTime1	pative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vpc 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz -2.5V to +2.5V 0% (about 140 mV hysteresis v hysteresis voltage) 1.310ms	Input Impedance = 1 MΩ DC
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Adjustment	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 5 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection Trigger Level Range GateTime1 GateTime2	spative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz -2.5V to +2.5V 0% (about 140 mV hysteresis v hysteresis voltage) 1.310ms 10.48ms	Input Impedance = 1 MΩ DC
Frequency Counter Function Frequency Resolution Frequency Range Period Measurement Voltage Range and Sensitivity DC Coupling AC Coupling Pulse Width and Duty Cycle M Frequency and Amplitude Ranges Pulse Width Duty Cycle Input Characteristics Input Signal Range Input Adjustment Input Trigger	Frequency, Period, Positive/Neg 7 digits/second (Gate Time = 1s 1 µHz to 200 MHz Measurement Range (non-modulating signal) DC Offset Range 1µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 100 MHz 100 MHz to 200 MHz 1 µHz to 5 MHz Min Pulse Width Pulse Width Resolution Measurement Range (display) Breakdown Voltage Coupling Mode High-frequency Rejection Trigger Level Range Trigger Sensitivity Range GateTime1 GateTime2 GateTime3	bative Pulse Width, Duty Cycle 5) 5ns to 16 days ±1.5 Vdc 50 mVRMS to ±2.5 Vac + dc 100 mVRMS to ±2.5 Vac + dc 50 mVRMS to ±2.5 Vpp 100 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vpp 50 mVRMS to ±2.5 Vac + dc ≥20 ns 5 ns 0% to 100% ±7Vac+dc AC On: Input Bandwidth = 250 kHz; Off: Input Bandwidth = 200 MHz -2.5V to +2.5V 0% (about 140 mV hysteresis v hysteresis voltage) 1.310ms 10.48ms 166.7ms	Input Impedance = 1 MΩ DC



Trigger Characteristics	
Trigger Input	
Level	TTL-compatible
Slope	Rising or falling (selectable)
Pulse Width	>100ns
Latency	Sweep: <100 ns (typical) Burst: <300 ns (typical)
Trigger Output	
Level	TTL-compatible
Pulse Width	> 60 ns (typical)
Maximum Frequency	1 MHz
Two-channel Characteristics -	- Phase Offset
Range	0° to 360°
Waveform Phase Resolution	0.03°
Defense Clash	
Reference Clock	
External Reference Input	40 MHz + FOLLE
Lock Range	10 MHz ± 50 Hz
Level	250 mVpp to 5 Vpp
Lock Time	<2s
Input Impedance (Typical)	1 kΩ, AC coupling
Internal Reference Output	T OWNERS 120 DV
Frequency	10 MHz ± 50 Hz
Level	3.3 Vpp
Input Impedance (Typical)	50 Ω, AC coupling
Sync Output	
Level	TTL-compatible
Impedance	50 Ω, nominal value

Overvoltage Protection

Occurred when:

- The instrument amplitude setting is greater than 2Vpp or the output offset is greater than |2Vpc| and the input voltage is greater than ±11.5 x (1 ± 5%)V (<10kHz).
- The instrument amplitude setting is lower than or equal to 2Vpp or the output offset is lower than or equal to |2Voc| and the input voltage is greater than ±3.5 × (1 ± 5%)V (<10kHz).

General Specifications		
Power Supply		
Power Voltage	100 V to 240 V (45 Hz to 440 Hz)	
Power Consumption	Lower than 40 W	
Fuse	250 V, T3.15 A	
Display		
Туре	3.5-inch TFT LCD	
Resolution	320 horizontal × RGB × 240 vertical resolution	
Color	16 M color	
Environment		
Temperature Range	Operating: 0°C to 50°C Non-operating: -40°C to 70°C	
Cooling Method	Fan cooling	
Humidity Range	Lower than 30°C : ≤95% relative humidity 30°C to 40°C : ≤75% relative humidity 40°C to 50°C : ≤45% relative humidity	
Altitude	Operating: below 3000 meters Non-operating: below 15,000 meters	
Mechanical		
Dimensions (W×H×D)	261.5 mm × 112 mm × 318.4 mm	
Weight	Without Package: 3.2 kg With Package: 4.5 kg	
Interfaces	USB Host, USB Device, LAN	
IP Protection	IP2X	
Calibration Interval	1 year recommended calibration interval	



	in line with EN61326-1:2006		
	IEC 61000-3-2:2000	±4.0kV (contact discharge) ±4.0kV (air discharge)	
	IEC 61000-4-3:2002	3 V/m (80 MHz to 1 GHz) 3 V/m (1.4 GHz to 2 GHz) 1 V/m (2.0 GHz to 2.7 GHz)	
	IEC 61000-4-4:2004	1 kV power lines	
EMC	IEC 61000-4-5:2001	0.5kV (Phase to Neutral) 0.5kV (Phase to PE) 1 kV (Neutral to PE)	
	IEC 61000-4-6:2003	3V,0.15MHz-80MHz	
	IEC 61000-4-11:2004	Voltage dip: 0 % UT during half cycle 0 % UT during 1 cycle 70 % UT during 25 cycles Short interruption: 0 % UT during 1 cycle	
Electrical Safety	Electrical Safety in line with USA:UL 61010-1:2012, Canada: CAN/CSA-C22.2 No. 61010-1-2012 EN 61010-1:2010		

Ordering Information

	Description	Order Number
Model	DG1022Z (25MHz, Dual-channel)	DG1022Z
	DG1032Z (30MHz, Dual-channel)	DG1032Z
	DG1062Z (60MHz, Dual-channel)	DG1062Z
Standard Accessories	Power Cord	-
	USB Cable	CB-USBA-USBB-FF-150
	BNC Cable	CB-BNC-BNC-MM-100
	Quick Guide	
	Resource CD (including User's Guide and etc.)	
Options	16Mpts Memory for Arb	Arb16M-DG1000Z
	Rack Mount Kit (for single instrument)	RM-1-DG1000Z
	Rack Mount Kit (for dual instruments)	RM-2-DG1000Z
	40dB Attenuator	RA5040K
	10W Power Amplifier	PA1011
	USB-GPIB Converter	USB-GPIB

